

# DF – EXP5 Power Supply Panel

# **Product Overview**

TheDF - EXP5is compact and cost effective 5 Amps power supply with build-in charger. It may be connect to the any 24 Volt Fire alarm control panel or may be standalone for the primary applications like Notification appliance circuit expansion or auxiliary power to support 24 Volt system accessories. It provides regulated and filtered 24 VDC power to NAC's and it also contains a battery charger capable of charging up to 14 Ah batteries.

#### **Features**

- Operates on 220V, A.C supply.
- Battery backup with built in charging.
- Low battery visual warning with audible tone.
- DC Output indication

#### **Electrical specification:**

#### Mains

220 VAC, 50 Hz +10%, -15%.

Wire size: 1.5 Sq. mm with 600V insulation

## **Battery (Lead Acid only)**

Charging Voltage: 27.9 VDC. Charging Current: 800mA Max System Quiescent Current: 35mA

#### **Output Voltage**

24VDC @ 5A Max.

### **Dimension**

350 Width x 400 Height x 100 Depth (mm)

## Weight

7 Kg Max.

# **Terminal Detail**



